

We can.

CWDM FILTER unit

FH-WF-A0511A



Feature

CWDM system

CWDM for 5wavelength

Low insertion loss

2.0dB@FH-WF-A0611A and O-MATRIX-502

Optical Backup

FH-WF-A0611A and O-MATRIX-602

仕 様

Item	Specification	
Number of optical port	COM :1 (adpter) others :6 (include fiber code)	
Optical connector	SC-APC	
Fiber code	SMF28 2.0 (PVC)	
Fiber	10/ 125 μ m	
Center wavelength	1310nm (downstream) 1470/1490/1510/1530nm (upstream)	
Bandwidth	Center wavwlength \pm 40nm(Downstream) Center wavelength \pm 6.5nm (upstream)	
Insertion loss	1310nm	0.8dB typ 2.0dB max
	1470nm	1.1dB typ 2.0dB max
	1490nm	1.0dB typ 2.0dB max
	1510nm	0.8dB typ 2.0dB max
	1530nm	0.7dB typ 2.0dB max
flatness	0.6dB typ 1.2dB max	
Stability of temp	Insertion loss	0.005dB/
	Wavelength	0.005nm/
Isolation	30dB@adjacent 50dB@non-adjacent 20dB@1310nm	
Optical return loss	50dB	
PDL	0.1dB	
Maximum Input power	24.7dBm	
length of fiber code	760mm	
Dimension	44.5 (W) x 103 (H) x 107 (D)	
Operating temp	- 10~ + 65	



安全に関するご注意

商品を安全にお使いいただくために、ご使用前に必ず「取扱説明書」をよくお読みください。

このカタログに記載の商品に関するお問い合わせは下記までお願いいたします。仕様および外観は、改良のため予告なく変更される事がありますので、あらかじめご了承ください。カタログと実際の色とは印刷の関係で、多少異なる場合があります。

古河電気工業株式会社 情報通信カンパニー ブロードバンド製品部 <http://www.furukawa.co.jp>

社会システム営業部 〒100- 8322 東京都千代田区丸の内2- 6- 1 (03)3286- 3173

技術ユニット 〒100- 8322 東京都千代田区丸の内2- 6- 1 (03)3286- 3145

カタログ掲載 :2005年1月現在