

We can.

CWDM FILTER unit

FH-WF-A0611A



Feature

CWDM system

CWDM for 6wavelength

Low insertion loss

2.0dB@FH-WF-A0611A and O-MATRIX-502

Optical Backup

FH-WF-A0611A and O-MATRIX-602

仕 様

Item		Specification
Number of optical port		COM :1 (adpter) others :6 (include fiber code)
Optical connector		SC-APC
Fiber code		SMF28 2.0 (PVC)
Fiber		10/ 125 μ m
Center wavelength		1550/1570nm (downstream) 1470/1490/1510/1530nm (upstream)
Bandwidth		Center wavelength \pm 6.5nm
Insertion loss	1550nm	0.5dB typ 1.0dB max
	1570nm	0.6dB typ 1.0dB max
	1470nm	1.2dB typ 1.5dB max
	1490nm	1.1dB typ 1.5dB max
	1510nm	0.9dB typ 1.5dB max
	1530nm	0.8dB typ 1.5dB max
flatness		0.7dB typ 1.4dB max
Stability of temp	Insertion loss	0.005dB/
	Wavelength	0.005nm/
Isolation		30dB@adjacent 50dB@non-adjacent
Optical return loss		50dB
PDL		0.1dB
Maximum Input power		24.7dBm
length of fiber code		760mm
Dimension		44.5 (W) \times 103 (H) \times 107 (D)
Operating temp		- 10 ~ + 65



安全に関するご注意

商品を安全にお使いいただくために、ご使用前に必ず「取扱説明書」をよくお読みください。

このカタログに記載の商品に関するお問い合わせは下記までお願いいたします。仕様および外観は、改良のため予告なく変更される事がありますので、あらかじめご了承ください。カタログと実際の色とは印刷の関係で、多少異なる場合があります。

古河電気工業株式会社 情報通信カンパニー ブロードバンド製品部 <http://www.furukawa.co.jp>

社会システム営業部 〒100- 8322 東京都千代田区丸の内2- 6- 1 (03)3286- 3173

技術ユニット 〒100- 8322 東京都千代田区丸の内2- 6- 1 (03)3286- 3145

カタログ掲載 :2005年1月現在